

# N... Contactor Relays

## a.c. Operated



N 40 E

1SB05 7862 2F0301



N 44 E

1SB05 7586 4F0301

### Ordering Details

Number of contacts		Type	Order code	Weight
1 <sup>st</sup> stack	2 <sup>nd</sup> stack			kg
		state coil voltage <input type="text"/> (see table below)	state coil voltage code <input type="text"/> <input type="text"/> (see table below)	Pack <sup>ing</sup> 1 piece

#### 4-pole, 1-stack

2	2	-	-	-	-	N 22 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 22	0.340
3	1	-	-	-	-	N 31 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 31	0.340
4	-	-	-	-	-	N 40 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 40	0.340

#### 8-pole, 2-stack

4	-	-	4	-	-	N 44 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 44	0.400
4	-	1	3	-	-	N 53 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 53	0.400
4	-	2	2	-	-	N 62 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 62	0.400
4	-	3	1	-	-	N 71 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 71	0.400
4	-	4	-	-	-	N 80 E <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 80	0.400

#### With overlapping of lagging / leading contacts

3	1	-	2	1	1	N 33/11 <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 39	0.400
4	-	1	1	1	1	N 51/11 <input type="text"/>	1SBH 141 001 R <input type="text"/> <input type="text"/> 59	0.400

#### Coil voltages and codes

Voltage	Voltage	Code
<input type="text"/> <input type="text"/> V - 50Hz	<input type="text"/> <input type="text"/> V - 60Hz	<input type="text"/> <input type="text"/>
24	24	8 1
48	48	8 3
110	110 ... 120	8 4
220 ... 230	230 ... 240	8 0
230 ... 240	240 ... 260	8 8
380 ... 400	400 ... 415	8 5
400 ... 415	415 ... 440	8 6

Other voltages: page 0/1.

>> Accessory Fitting Details ..... page 3/8	>> General - Approvals ..... section 7
>> Technical Data ..... page 3/10	>> Terminal Marking and Positioning ..... section 8
>> Auxiliary Contacts for Safety Circuits ..... page 3/15	>> Dimensions ..... section 9

3