

Datasheet

RS Pro Straight 50Ω RF Adapter BNC Socket to BNC Socket

RS Stock No: **546-4522**



Product Details

RS Pro RF adapter has BNC socket connector on both the ends that comes with an impedance of 50 Ω. The RF adapter has straight body orientation and is made of copper material.

Features and Benefits

- Nominal impedance of 50Ω
- Copper contacts
- Straight orientation

Specifications:

Adapter Type A	BNC
Adapter Type B	BNC
Adapter Type	BNC Socket to BNC Socket
Body Orientation	Straight
Body Plating	Silver
Contact Material	Copper
Contact Plating	Silver
Gender A	Socket
Gender B	Socket
Impedance	50 Ω
Length	32.5 mm
Operating Frequency	0 to 4 GHz
Body Material	Brass
Insulation Material	PTFE
Operating Temperature	-65 to +165°C
Voltage Rating	500 V