



Datasheet

ENGLISH

Stock No: 526-5785

RS Pro Straight PCB Mount SMA End Launcher Connector, jack, Solder Termination



Product Details

This range of RS Pro RF coaxial 50 Ohm SMA edge mount end launchers have a DC-18 GHz frequency range. Designed for efficient mounting to printed circuit boards, these RF coaxial 50 Ohm SMA edge mount end launchers have a gold plated brass body, teflon insulator and gold plated contact.



ENGLISH

The RS Range of RF Coaxial End Launchers includes the following:

- Stock number 526-5757 is 9.52 x 9.52mm square and accepts a PCB thickness of 1.7mm
- Stock number 526-5763 is 9.52 x 9.52mm square and accepts a PCB thickness of 1.2mm
- Stock number 526-5785 is 6.35 x 6.35mm square and accepts a PCB thickness of 1.7mm
- Stock number 526-5791 is 6.35 x 6.35mm square and accepts a PCB thickness of 1.2mm

Specifications:

Gender	Female
Mounting Type	PCB Mount
Body Orientation	Straight
Termination Method	Solder
Polarity	Normal
Operating Frequency	0 → 18GHz
Body Plating	Gold
Size	Subminiature
Contact Material	Beryllium Copper