

**Inrush Characteristics for PCE - 011 Twin High Frequency Electronic Ballasts- 1.5mm Installation Conductor**

**Inrush Simulation PC 2x58 E011**

No.of Ballasts	Duration in $\mu$ s	Current in A
1	166	50
5	263	153
10	337	212
15	414	242
20	483	257

**Inrush Simulation PC 2x36 E011**

No.of Ballasts	Duration in $\mu$ s	Current in A
1	150	44
5	213	130
10	279	187
15	339	216
20	397	231
25	454	239
30	489	242

**Inrush Simulation PC 2x18 E011**

No.of Ballasts	Duration in $\mu$ s	Current in A
1	128	39
5	188	108
10	233	162
15	297	192
20	315	209
25	367	218
30	400	222