

Bobbin  
**FS-2E-4220-10**



## Advantages


Cost saving and easy compilation of components for pattern construction through unification

On request, wound inductors to EN61558-2-16 and EN60950 or vacuum potted

## Applications

Transformers and reactors in switch mode power supplies

## Approvals



## Bobbin FS-2E-4220-10

Electrical data

| Type         | FS-2E-4220-10                    |
|--------------|----------------------------------|
| General data |                                  |
| for core     | Rynite FR530(L)<br>FS-1E-4220-00 |
| Environment  | F                                |
| Notes        | ISO 2768-m                       |

Mechanical data

| Type                 | FS-2E-4220-10       |
|----------------------|---------------------|
| Measures and weights |                     |
| Winding width        | vertical<br>26.0 mm |
| Winding hight        | 7.0 mm              |
|                      | 1                   |
|                      | 6,2                 |
|                      | 27,5                |
|                      | 5                   |
|                      | 18                  |

Subjects to change.