

LAD5C12

TeSys - connection module - for reversing motor starter - 9...32 A



Main

Range of product	TeSys
Device short name	LAD5C
Product or component type	Connection module
Accessory / separate part category	Connection accessory
Function	Connection to PLC I/O module
Control circuit voltage	24 V DC

Complementary

Mounting location	Front
Connector type	RJ45
Monitoring and control	Modicon TM3 Modicon Telefast Modicon STB
Product compatibility	GV2ME GV2P LC1D LC2D GV2DM
Motor starter type	Reversing
Power rated current	9...32 A on AC-3
Starter control terminal	Screw clamp terminals
Product certifications	CE CUL
Height	204 mm
Width	90 mm
Depth	38 mm
Product weight	67 g
Quantity per set	3

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.